



ELECTRICAL RATINGS

ELECTRICAL RATINGS	
Parameter	Rating
Input Voltage	120 VAC, 50/60Hz
Input Power (max)	166W
Output Power	150W
Relay Lock Outputs	4 @ 3A Fused
Auxiliary Outputs	8 @ 3A Fused
Maximum Charge Current	FP075: 1A, 40AH maximum
Low Power Disconnect	at 70% of battery voltage
Systems BTU/Hr	33 BTU/Hr
Operating Temperature	32 to 122F (0 to +50C)
Efficiency	85% 120VAC 60Hz In, Full Load
Agency Approvals	UL294, UL603, UL1076, ULC
	S318, ULC S319, CSA C22.2
	#205, FCC Part 15, Subpart B,
	CSFM IEC 62368-1:2014, EN
	55032:2015, EN6100-3-2:2014,
	EN6100-3-3:2013,
	EN55024:2010+A1:2015, BIS
	IS13252(Part 1):2010, REACH
	209, ROHS 3

OVERVIEW

Standard Power Systems provide FlexPower power modules in a secure UL listed solution. Standard Power features include:

- Built in Fire Alarm disconnect unlocks doors on a fire alarm
- Low battery cutoff protects batteries from deep discharge
- · Dedicated fast charger prolongs battery life
- Enhanced surge immunity for input/output protection
- Locksafe optimized voltages provide long-term lock protection
- OutSmart Visual LED notification (12V/Green, 24V/Blue)
- Network ready with optional LifeSafety Power NetLink® module
 - Monitor power supply and battery in NetLink dashboard
 - · Remote test batteries
- Lifetime Warranty LifeSafety Power's quality commitment

SYSTEM DETAILS

- 2 x FP075 150W Total Output, 120 VAC Input, AC Fault and System Fault form C contacts may be triggered by low/no battery, short to earth ground, power supply failure, or blown fuse
- 1 x C4 (4 Relay Lock Outputs) 3A fused outputs, programmable for failsafe/failsecure, FAI, NC/NO input, voltage or dry output per zone. Dual buss voltage selection by zone, OutSmart dual color LEDs
- 1 x D8 (8 Auxiliary Outputs) 3A fused Outputs, dual buss voltage selection by zone, OutSmart dual color LEDs
- **E1 Enclosure** Size: 14.0H x 12.0W x 4.5D in (35.56 x 30.48 x 11.43 cm)
 - o Enclosure E1
- System Weight 9.60 lbs (4.35kg)

ORDERING

FP075/75-C4D8E1

120 VAC, 150W, 4 Lock, 8 Aux

AGENCY LISTINGS

US | Canada | Mexico | Europe | UK | India | Australia | New Zealand | RoHS

















LifeSafety Power