



#### ELECTRICAL RATINGS

Parameter	Rating
Input Voltage	120 VAC, 50/60Hz
Input Power (max)	83W
Output Power	75W
Managed Lock Outputs	8 @ 2.5A Class 2 Power Limited
Maximum Charge Current	FPO75: 1A, 40AH maximum
Low Power Disconnect	at 70% of battery voltage
Systems BTU/Hr	33 BTU/Hr
Operating Temperature	32 to 122F (0 to +50C)
Efficiency	85% 120VAC 60Hz In, Full Load
Agency Approvals	UL294, UL1076, UL2610, ULC S318, ULC S319, CSA C22.2 #107.1, FCC Part 15, Subpart B, CSFM IEC 62368-1:2014, EN 55032:2015, EN6100-3-2:2014, EN6100-3-3:2013, EN55024:2010+A1:2015, BIS IS13252(Part 1):2010, NOM-001-SCFI-1933, REACH 209, ROHS 3, RCM AS/NZS 4417.1, SAA AS/NZS 62368.1:2018

#### OVERVIEW

Mercury ProWire Power Systems combine FlexPower modules alongside access control hardware in one compact and secure UL listed solution. ProWire systems are prewired for power to the access control modules, faults, tamper switch, lock control wiring (where applicable) and communication. ProWire features include:

- Built in Fire Alarm disconnect unlocks doors on a fire alarm
- Low battery cutoff protects batteries from deep discharge
- Dedicated fast charger prolongs battery life
- Enhanced surge immunity for input/output protection
- Locksafe optimized voltages provide long-term lock protection
- OutSmart Visual LED notification (12V/Green, 24V/Blue)
- Network ready with optional LifeSafety Power NetLink® module
  - Monitor power supply and battery in NetLink dashboard
  - Remote test batteries
- Lifetime Warranty LifeSafety Power's quality commitment

#### SYSTEM DETAILS

- **1 x FPO75** 75W Total Output, 120 VAC Input, AC Fault and System Fault form C contacts may be triggered by low/no battery, short to earth ground, power supply failure, or blown fuse
- **1 x M8P (8 Managed Lock Outputs)** 2.5A Class 2 power limited outputs, programmable for failsafe/failsecure, remote power cycle, monitor voltage and current on each output, programmable limits, dual buss voltage selection by zone, cycle count by zone, bi-color output LEDs verify voltage setting
- **1 x NL4 NetLink Module** Provides remote monitoring of power supply and battery set, remote battery testing, temperature monitoring, tamper switch monitoring, email/SNMP alerts on faults, compatible with MSM Enterprise
- **RGM/W4-C Enclosure** Size: 3.5H x 19.0W x 20.5D in (8.89 x 48.26 x 52.07 cm)
  - **Enclosure RG**
  - **ProWire RGM/W4-C** Prewired for 4 Doors, 2xMR52
  - **Routing Kit Tie-Wrap, RGM**
- **System Weight** 26.75 lbs (12.13kg)

#### ORDERING

RGM75-M8PNZ/T4-C	120 VAC, 75W
------------------	--------------

#### AGENCY LISTINGS

US | Canada | Mexico | Europe | UK | India | Australia | New Zealand | RoHS



#### LifeSafety Power

10027 S. 51st Street, Suite 102  
Phoenix, AZ 85044 USA  
(888) 577-2898  
info@lifesafetypower.com

#### Disclaimer:

This datasheet was generated programmatically by LifeSafety Power's Online Product Generator on 03/28/2025. Because of this, it may be possible that the model depicted is not possible for LifeSafety Power to build. It is the responsibility of the viewer of this datasheet to confirm that the model depicted is within the limitations of the product line. Contact LifeSafety Power for confirmation of fitment or compatibility. Specifications subject to change without notice.