

Cloud Managed Gigabit Ethernet Low Power PoE Switch

NSW3000-17GT1GP1GC-LPOE-IN

Overview

The NSW3000 series Gigabit Ethernet PoE switch is a cloud managed switch self-developed by Uniview with high performance, easy to use and maintain. The product adopts the leading high performance hardware architecture and industrial design concepts to enhance the environmental adaptability of the network. It provides a lightweight 2 layers of network basic configuration, including port mirroring, port anti-loop, VLAN, link aggregation, flow control, etc. It supports auto-discovery of connected video devices and generation of network topology; supports unified management and configuration on the software for rapid maintenance of multiple devices; and supports viewing the device status and managing devices on the Web or app. The switch meets the user's requirements to access the network with highly reliability and low cost, widely used in scenarios such as stores, supermarkets, enterprises, campuses, etc.



Features

- Supports unified configuration, management, and search on the software, convenient for rapid operation and maintenance of multiple devices; supports automatically discovering the connected video devices and generating a network topology on the software.
- Supports Web login, and device configuration and management on the Web interface;
- Supports visiting the cloud by scanning the QR code. Allows to view the device status and network topology in real time on the app, and remotely restart the PoE power supply.
- Supports PoE power supply and allows to view the power; allows to enable or disable PoE power supply for the powered device; allows

up to 250m power supply using a standard network cable.

- Supports the extend mode for up to 250m communication range and 10Mbps auto-negotiation rate.
- Allows to report port abnormal alarms to the software for realtime monitoring.
- Supports port priority. The packets received by the priority port will be forwarded first when the switch is fully loaded and the priority port will be powered first when the PoE power supply is full.
- All metal casing, secure and reliable.

Specifications

| Model | NSW3000-17GT1GP1GC-LPOE-IN |
|------------------------|--|
| Hardware Specification | |
| Ports Type | 16 x 10/100/1000Mbps PoE port (RJ45) 1 x 10/100/1000Mbps port (RJ45) 1 x Gigabit SFP 1 x Gigabit Combo |
| Standards | IEEE802.3, IEEE802.3u, IEEE802.3z, IEEE802.3ab, IEEE802.3x, IEEE802.3af, IEEE802.3at, IEEE802.3az |
| Switching capacity | 38Gbps |
| Forwarding performance | 28.272Mpps |
| Packet Buffer | 4 M bit |
| MAC | 8K |
| Weight | 2.03kg |
| Dimensions (W×D×H) | 440mm x 195mm x 44mm |
| Power Supply | AC 100V to 240V, 50/60Hz |
| Max.Power | 165W |
| Max.PoE Power | Maximum total power: 150W Maximum PoE power for single port: 30W Mode A, 1/2+, 3/6- Mode B, 4/5+, 7/8- |
| Prior Ports | 1 to 8 |
| Cooling Fans | 0 |
| Operating temperature | 0 °C to 40 °C (32 °F to 104 °F) |
| Operating humidity | 10%~90% (non-condensing) |
| Storage Temperature | -40 °C to 70 °C |
| Storage Humidity | 5% to 90% RH, noncondensing |
| Indicator | POWER Off: No AC input, Power On (Green): Normal power input, Power On (Yellow): The total PoE power is higher than 85% of the total power of the device, PoE Off: No PoE power supply, PoE Steady on: PoE power supply is normal, LINK/ACT Off: No link, LINK/ACT Steady on: Linked, LINK/ACT Flashing: Transmitting data, PoE-MAX off: The POE power supply power of the whole machine is less than 80% of the specification, PoE-MAX Steady on : The POE power supply power of the whole machine is greater than 85% of the specification |
| Software Specification | |

| | |
|----------------|--|
| Ethernet | <p>Supports full duplex, half duplex, and auto-negotiation working modes.</p> <p>Supports port auto-negotiation rate.</p> <p>Supports port priority flow control.</p> <p>Supports a link aggregation group (consist of two uplink ports)</p> <p>Supports port flow statistics</p> <p>Supports enabling/disabling ports</p> |
| VLAN | Supports both access and trunk modes; allows up to 32 VLANs with IDs from 1 to 4094 |
| MAC | <p>Support (up to 8K) .</p> <p>Supports clearing the dynamic MAC address</p> |
| POE | <p>Allows to view PoE status and power.</p> <p>Allows to enable/disable PoE power supply.</p> |
| Loop Detection | Loop Detection |
| QoS | <p>Supports port rate limitation.</p> <p>Supports broadcast storm control.</p> |
| System | <p>Allows to view the device name, device model, serial number, current version, IP address, MAC address, DNS, operation time, etc.</p> <p>Allows to edit and manage the IP address and device name</p> <p>Supports single-user management, user authentication, and password modification</p> <p>Supports manual time configuration and NTP</p> <p>Allows to view other switches information on the same network, up to 32 switches</p> <p>Allows to view the connected video devices information, up to 64 devices</p> |
| Security | <p>Supports port isolation (only for the downlink ports)</p> <p>Supports locking login IP address, up to 64 addresses can be locked</p> |
| Maintenance | <p>Supports N: 1 port mirroring</p> <p>Supports unified software configuration, management, and search</p> <p>Supports discovering the connected video devices and generating a network topology on the software.</p> <p>Supports device upgrade, factory settings restoration, configuration import, configuration export, logs export, and device restart on the software.</p> |

Ordering Info

| Product Model | Description |
|----------------------------|--|
| NSW3000-17GT1GP1GC-LPOE-IN | NSW3000-17GT1GP1GC-LPOE-IN Gigabit Cloud Management PoE Switch |

Zhejiang Uniview Technologies Co., Ltd.

No. 369, Xietong Road, Xixing Sub-district, Binjiang District, Hangzhou City, 310051, Zhejiang Province, China

Email: overseasbusiness@uniview.com; globalsupport@uniview.com

<http://www.uniview.com>

©2024-2025 Zhejiang Uniview Technologies Co., Ltd. All rights reserved.

*Product specifications and availability are subject to change without notice.

*Despite our best efforts, technical or typographical errors may exist in this document. Uniview cannot be held responsible for any such errors and reserves the right to change the contents of this document without prior notice.